

OUTLETS

Instantly make any household plug-in device, like lamps, appliances and electronics, part of the Control4 system by turning a standard outlet into two smart outlets.

FEATURES:

- *Reduce energy waste and lower your utility bills by setting lights for maximum energy efficiency.*
- *Personalize your lights to turn on and off—and dim or ramp—to create whatever mood you desire.*
- *Turn standard outlets into a smart way to control two plug-in lamps or other devices, no special wiring required.*

Control4® Outlet Dimmer and Switch



Control4® Wireless Outlet Dimmer LOZ-5D1 Control4® Wireless Outlet Switch LOZ-5SI

Enjoy the benefits of smart lighting with easy-to-use, affordable Control4 Dimmers and Switches. Lower your utility bills, increase your bulb life, ease your environmental conscience, and enjoy the convenience of pre-determined, one-touch Lighting Scenes.

Control4 Outlet Dimmers and Switches easily plug into outlets to offer complete control of your plug-in lights. Control4 smart lighting control solutions are accessible to everyone, and let you add rooms and functions when it makes sense for you.

- Reduce energy waste and lower your utility bills by setting lights for maximum energy efficiency.
- Personalize your lights to create whatever mood you desire: gentle wake-up scenes, romantic mood lighting, darkened home theater for Friday night movies, or “welcome home” to make sure you and your family never enter a dark house again.
- Turn standard outlets into a smart way to control two plug-in lamps or other devices, no special wiring required.

Control4® Wireless Outlet Dimmer and Switch

	Control4® Wireless Outlet Dimmer	Control4® Wireless Outlet Switch
Model Number	LOZ-5D1	LOZ-5S1
Power Requirements	120 VAC +/- 10% 60/50 Hz	120 VAC +/- 10% 60/50 Hz
Power Consumption	1.4 W - LEDs Off	1.4 W - LEDs Off
Supports No-Neutral Wiring Option	No	No
Minimum Load	25 W	N/A
Incandescent/Tungsten/Halogen	700 W Total Across Both Outlets	600W Each Outlet
Fluorescent	N/A	5.8 A Electronic Ballast Each Outlet
Compact Fluorescent (CFL)	N/A	5.8 A Each Outlet
Electronic Low Voltage (ELV)	N/A	5.8 A Each Outlet
Magnetic Low Voltage (MLV)	N/A	1000 VA Each Outlet 15 A Total Across Both Outlets
Motor	N/A	1/4 HP (5.8 FLA) Each Outlet
Multi-Gang Derating	N/A	N/A
Control Communications	ZigBee (802.15.4) Mesh Networking	ZigBee (802.15.4) Mesh Networking
Operational Temperature	32°F - 104°F (0°C - 40°C)	32°F - 104°F (0°C - 40°C)
Humidity	5% - 95% Non-Condensing	5% - 95% Non-Condensing
Storage	-4°F - 158°F (-20°C - 70°C)	-4°F - 158°F (-20°C - 70°C)
Dimensions (H x W x D)	4.5" x 2.6" x 1.6" (114 mm x 66 mm x 41 mm)	4.5" x 2.6" x 1.6" (114 mm x 66 mm x 41 mm)
Weight	8.0 oz (227 g)	8.0 oz (227 g)
Available Colors	WH	WH

Control4® Outlet Dimmer and Switch



Control4® Wireless Outlet Dimmer LOZ-5D1

Control4® Wireless Outlet Switch LOZ-5SI

Enjoy the benefits of smart lighting with easy-to-use, affordable Control4 Dimmers and Switches. Lower your utility bills, increase your bulb life, ease your environmental conscience, and enjoy the convenience of pre-determined, one-touch Lighting Scenes.

Control4 Outlet Dimmers and Switches easily plug into outlets to offer complete control of your plug-in lights. Control4 smart lighting control solutions are accessible to everyone, and let you add rooms and functions when it makes sense for you.

- Reduce energy waste and lower your utility bills by setting lights for maximum energy efficiency.
- Personalize your lights to create whatever mood you desire: gentle wake-up scenes, romantic mood lighting, darkened home theater for Friday night movies, or “welcome home” to make sure you and your family never enter a dark house again.
- Turn standard outlets into a smart way to control two plug-in lamps or other devices, no special wiring required.

Control4® Wireless Outlet Dimmer and Switch

	Control4® Wireless Outlet Dimmer	Control4® Wireless Outlet Switch
Model Number	LOZ-5D1	LOZ-5S1
Power Requirements	120 VAC +/- 10% 60/50 Hz	120 VAC +/- 10% 60/50 Hz
Power Consumption	1.4 W - LEDs Off	1.4 W - LEDs Off
Supports No-Neutral Wiring Option	No	No
Minimum Load	25 W	N/A
Incandescent/Tungsten/Halogen	700 W Total Across Both Outlets	600W Each Outlet
Fluorescent	N/A	5.8 A Electronic Ballast Each Outlet
Compact Fluorescent (CFL)	N/A	5.8 A Each Outlet
Electronic Low Voltage (ELV)	N/A	5.8 A Each Outlet
Magnetic Low Voltage (MLV)	N/A	1000 VA Each Outlet 15 A Total Across Both Outlets
Motor	N/A	1/4 HP (5.8 FLA) Each Outlet
Multi-Gang Derating	N/A	N/A
Control Communications	ZigBee (802.15.4) Mesh Networking	ZigBee (802.15.4) Mesh Networking
Operational Temperature	32°F - 104°F (0°C - 40°C)	32°F - 104°F (0°C - 40°C)
Humidity	5% - 95% Non-Condensing	5% - 95% Non-Condensing
Storage	-4°F - 158°F (-20°C - 70°C)	-4°F - 158°F (-20°C - 70°C)
Dimensions (H x W x D)	4.5" x 2.6" x 1.6" (114 mm x 66 mm x 41 mm)	4.5" x 2.6" x 1.6" (114 mm x 66 mm x 41 mm)
Weight	8.0 oz (227 g)	8.0 oz (227 g)
Available Colors	WH	WH